



Supported media list

- **BD-R SL DL on BDR-S11 and BDR-211 series**
- **BD-R XL on BDR-S11 and BDR-211 series**
- **BD-RE SL DL on BDR-S11 and BDR-211 series**
- **BD-RE XL on BDR-S11 and BDR-211 series**
- **DVD-R on BDR-S11 and BDR-211 series**
- **DVD-RW on BDR-S11 and BDR-211 series**
- **DVD-RAM on BDR-S11 and BDR-211 series**
- **DVD+R on BDR-S11 and BDR-211 series**
- **DVD+RW on BDR-S11 and BDR-211 series**
- **CD-R on BDR-S11 and BDR-211 series**
- **CD-RW on BDR-S11 and BDR-211 series**



Supported media list of BD-R SL DL on BDR-S11 and BDR-211 series

BD-R (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status												Remarks		
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	CAV	CAV	CAV	CAV	CAV
1	CMC	"CMCMAGBA2"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
2	MAXELL	"MAXELLRS1"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
3	Panasonic	"MEI_T01"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
4	PHILIPS	"PHILIPR02"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
5	SONY	"SONY_N01"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
6	SONY	"SONY_NS1"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
7	TDK	"TDKBBLDRBA"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
8	TDK	"TDKBBLDRDA"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-
9	MKM	"VERBATIMa"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-	-

In case of unknown MID, the writing speed is limited to 2x.

BD-R (LtoH 2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status												Remarks	
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	CAV	CAV	CAV	CAV
1	MKM	"VERBATIMw"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-

In case of unknown MID, the writing speed is limited to 2x.

BD-R (4x format disc)

Writing speed : 2x, 4x, 6x, 8x, 10x, 12x

No.	Maker	Manufacturer ID	Strategy Status												Remarks	
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	CAV	CAV	CAV	CAV
1	CMC	"CMCMAGBA3"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
2	Infomedia	"INFOMER30"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
3	Infosource	"ISMMBDR01"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
4	LGE	"LGEBRAS04"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
5	Panasonic	"MEI_T02"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
6	Millenniata	"MILLENMR1"	Y	Y	-	-	-	-	-	-	-	-	-	-	-	-
7	PHILIPS	"PHILIPR04"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
8	PRODISC	"PRODISCR0"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
9	RITEK	"RITEK_BR2"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
10	SONY	"SONY_NN2"	Y	-	-	Y	Y	Y	Y	Y	-	-	-	-	-	-
11	SONY	"SONY_NS2"	Y	Y	-	-	-	-	-	-	-	-	-	-	-	-
12	TDK	"TDKBBLDRBB"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
13	Umedisc	"UMEBDR014"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
14	MKM	"VERBATIMc"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-

In case of unknown MID, the writing speed is limited to 2x and 4x.



Supported media list of BD-R SL DL on BDR-S11 and BDR-211 series

BD-R (LtoH 4x format disc)

Writing speed : 2x, 4x

No.	Maker	Manufacturer ID	Strategy Status										Remarks
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	
1	RITEK	"RITEK_BO1"	Y	Y	-	-	-	-	-	-	-	-	
2	TAIYOYUDEN	"TYG-BDY03"	Y	Y	-	-	-	-	-	-	-	-	
3	Umedisc	"UMEBDR114"	Y	Y	-	-	-	-	-	-	-	-	
4	MKM	"VERBATIMv"	Y	Y	-	-	-	-	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2x.

BD-R (6x format disc)

Writing speed : 2x, 4x, 6x, 8x, 10x, 12x, 14x, 16x

No.	Maker	Manufacturer ID	Strategy Status										Remarks
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	
1	CMC	"CMCMAGBA5"	Y	-	-	Y	Y	Y	Y	Y	-	-	
2	Infomedia	"INFOMER40"	Y	-	-	Y	Y	Y	-	-	-	-	
3	LGE	"LGEBRAS06"	Y	-	-	Y	Y	Y	Y	-	-	-	
4	MBI	"MBI_R06"	Y	-	-	Y	Y	Y	Y	-	-	-	
5	Panasonic	"MEI_RA1"	Y	-	-	Y	Y	Y	Y	Y	-	-	
6	OPTODISC	"OTCBDR002"	Y	-	-	Y	Y	Y	-	-	-	-	
7	PRODISC	"PRODISCR1"	Y	-	-	Y	Y	Y	Y	-	-	-	
8	RITEK	"RITEK_BR3"	Y	-	-	Y	Y	Y	Y	-	-	-	
9	RITEK	"RITEK_BR3"	Y	-	-	Y	Y	Y	Y	Y	-	-	
10	RITEK	"RITEK_BR4"	Y	-	-	Y	Y	Y	Y	Y	-	Y	
11	SONY	"SONY_NN3"	Y	-	-	Y	Y	Y	Y	Y	-	Y	
12	TDK	"TDKBBLDRBD"	Y	-	-	Y	Y	Y	Y	-	-	-	
13	Umedisc	"UMEBDR016"	Y	-	-	Y	Y	Y	-	-	-	-	
14	MKM	"VERBATIMe"	Y	-	-	Y	Y	Y	Y	Y	-	Y	

In case of unknown MID, the writing speed is limited to 2x and 4x.

BD-R (LtoH 6x format disc)

Writing speed : 2x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Strategy Status										Remarks
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	
1	JVC	"JVC-AMS6L"	Y	-	-	Y	Y	Y	-	-	-	-	
2	MAXELL	"MAXELLRS2"	Y	-	-	Y	Y	Y	-	-	-	-	
3	MBI	"MBI_F06"	Y	Y	Y	-	-	-	-	-	-	-	
4	RITEK	"RITEK_BO2"	Y	Y	Y	-	-	-	-	-	-	-	
5	TAIYOYUDEN	"TYG-BDY05"	Y	-	-	Y	Y	Y	-	-	-	-	
6	Umedisc	"UMEBDR116"	Y	Y	Y	-	-	-	-	-	-	-	
7	MKM	"VERBATIMu"	Y	Y	Y	-	-	-	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2x.



Supported media list of BD-R SL DL on BDR-S11 and BDR-211 series

BD-R(DL) (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status												Remarks	
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	CAV	CAV	CAV	CAV
1	Panasonic	"MEI_T01"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-
2	TDK	"TDKBLDRFA"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-
3	MKM	"VERBATIMb"	Y	-	-	-	-	-	-	-	-	-	-	-	-	-

In case of unknown MID, the writing speed is limited to 2x.

BD-R(DL) (4x format disc)

Writing speed : 2x, 4x, 6x, 8x, 10x

No.	Maker	Manufacturer ID	Strategy Status												Remarks	
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	CAV	CAV	CAV	CAV
1	Panasonic	"MEI_T02"	Y	-	-	Y	Y	Y	Y	-	-	-	-	-	-	-
2	RITEK	"RITEK_DR2"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
3	SONY	"SONY_ND4"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
4	TDK	"TDKBLDRFB"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
5	MKM	"VERBATIMd"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-

In case of unknown MID, the writing speed is limited to 2x and 4x.

BD-R(DL) (6x format disc)

Writing speed : 2x, 4x, 6x, 8x, 10x, 12x, 14x

No.	Maker	Manufacturer ID	Strategy Status												Remarks	
			2x	4x	6x	4x	6x	8x	10x	12x	14x	16x	CAV	CAV	CAV	CAV
1	CMC	"CMCMAGDI6"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
2	Panasonic	"MEI_RB1"	Y	-	-	Y	Y	Y	Y	Y	Y	-	-	-	-	-
3	RITEK	"RITEK_DR3"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
4	SONY	"SONY_ND6"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
5	TDK	"TDKBLDRFD"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-
6	MKM	"VERBATIMf"	Y	-	-	Y	Y	Y	-	-	-	-	-	-	-	-

In case of unknown MID, the writing speed is limited to 2x and 4x.



Supported media list of BD-R XL on BDR-S11 and BDR-211 series

Notice : BDR-211DBK and BDR-211BK don't support BD-R XL.

BD-R(TL) (4x format disc)

Writing speed : 2x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	CAV	CAV	CAV	4x	
1	Panasonic	"PAN_RC4"	Y	Y	-	-	-	-	-	-	
2	RITEK	"RITEK_TL2"	Y	Y	Y	-	-	-	-	-	
3	TDK	"TDKBBLDRNC"	Y	Y	Y	Y	-	-	-	-	
4	MKM	"VERBATIMk"	Y	Y	Y	-	-	-	-	-	

In case of unknown MID, the drive doesn't support writing

BD-R(QL) (4x format disc)

Writing speed : 2x, 4x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	CAV	CAV	CAV	4x	
1	SONY	"SONY_NQ1"	Y	Y	Y	-	-	-	-	-	

In case of unknown MID, the drive doesn't support writing



Supported media list of BD-RE SL DL on BDR-S11 and BDR-211 series

BD-RE (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status 2x	Remarks
1	CMC	"CMCMAGCN2"	Y	
2	Imation	"IMATN_E_2"	Y	
3	JVC	"JVCRE1101"	Y	
4	LGE	"LGBEBRES01"	Y	
5	MAXELL	"MAXELLES1"	Y	8cm
6	MBI	"MBI_E02"	Y	
7	Panasonic	"MEI_T01"	Y	
8	PHILIPS	"PHILIPW02"	Y	
9	RITEK	"RITEK_BW1"	Y	
10	SONY	"SONY_ES1"	Y	
11	TDK	"TDKBBLDWBA"	Y	
12	TDK	"TDKBBLDWDA"	Y	8cm
13	Umedisc	"UME BRE012"	Y	
14	MKM	"VERBATIM0"	Y	

In case of unknown MID, the writing speed is limited to 2x.

BD-RE(DL) (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status 2x	Remarks
1	Panasonic	"MEI_T01"	Y	
2	RITEK	"RITEK_DW1"	Y	
3	SONY	"SONY_ED4"	Y	
4	TDK	"TDKBBLDWfa"	Y	
5	MKM	"VERBATIM1"	Y	

In case of unknown MID, the writing speed is limited to 2x.



Supported media list of BD-RE XL on BDR-S11 and BDR-211 series

Notice : BDR-211DBK and BDR-211BK don't support BD-RE XL.

BD-RE(TL) (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status 2x	Remarks
1	Panasonic	"PAN EC2"	Y	
2	SONY	"SONY ET2"	Y	

In case of unknown MID, the drive doesn't support writing



Supported media list of DVD-R on BDR-S11 and BDR-211 series

DVD-R Ver2.0 (1x format disc)

Writing speed : 1x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	

In case of unknown MID, the writing speed is limited to 1x.

DVD-R Ver2.0 Rev1.0 (4x format disc)

Writing speed : 2x, 4x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	

In case of unknown MID, the writing speed is limited to 2x and 4x.

DVD-R Ver2.0 Rev2.0 (8x format disc)

Writing speed : 4x, 6x, 8x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	
1	CMC	"CMC MAG. AE1"	-	Y	Y	Y	-	-	-	-	
2	DST	"Dvsn-80"	-	Y	Y	Y	-	-	-	-	
3	Gigastorage	"GSC003"	-	Y	Y	Y	-	-	-	-	
4	Gigastorage	"GSC004"	-	Y	Y	Y	-	-	-	-	
5	Infomedia	"INFOMEDIAR20"	-	Y	Y	Y	-	-	-	-	
6	Infosource	"ISSM R01"	-	Y	Y	Y	-	-	-	-	
7	Lead Data	"LEADDATA S03"	-	Y	Y	Y	-	-	-	-	
8	MKM	"MCC 02RG20 "	-	Y	Y	Y	-	-	-	-	
9	Must	"MUST 003"	-	Y	Y	Y	-	-	-	-	
10	MAXELL	"MXL RG03"	-	Y	Y	Y	-	-	-	-	
11	OPTODISC	"OPTODISCR008"	-	Y	Y	Y	-	-	-	-	
12	PRINCO	"PRINCO8X02"	-	Y	Y	Y	-	-	-	-	
13	PRODISC	"ProdiscF01"	-	Y	Y	Y	-	-	-	-	
14	PRODISC	"ProdiscS04 "	-	Y	Y	Y	-	-	-	-	
15	RITEK	"RITEKG05"	-	Y	Y	Y	-	-	-	-	
16	SONY	"SONY08D1"	-	Y	Y	Y	-	-	-	-	
17	TCL	"TCLDS01"	-	Y	Y	Y	-	-	-	-	
18	TMI	"TMI8X001"	-	Y	Y	Y	-	-	-	-	
19	TDK	"TTG02"	-	Y	Y	Y	-	-	-	-	
20	TDK	"TTH01"	-	Y	Y	Y	-	-	-	-	
21	TAIYOYUDEN	"TYG02"	-	Y	Y	Y	-	-	-	-	
22	Umedisc	"UME01"	-	Y	Y	Y	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2x and 4x.



Supported media list of DVD-R on BDR-S11 and BDR-211 series

DVD-R Ver2.0 Rev6.0 (16x format disc)

Writing speed : 4x, 6x, 8x, 12x, 16x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	
1	CMC	"CMC MAG. AM3"	-	Y	-	-	Y	Y	Y	Y	
2	CMC	"CMC MAG. AM4"	-	Y	-	-	Y	Y	Y	Y	
3	Daxon	"DAXON016S"	-	Y	-	-	Y	Y	Y	Y	
4	DST	"Dvsn-160"	-	Y	-	-	Y	Y	Y	Y	
5	FTI	"FTI RG16"	-	Y	-	-	Y	Y	Y	Y	
6	FUJIFILM	"FUJIFILM04"	-	Y	-	-	Y	Y	Y	Y	
7	FUJIFILM	"FUJIFILM05"	-	Y	-	-	Y	Y	Y	Y	
8	Gigastorage	"GSC005"	-	Y	-	-	Y	Y	Y	Y	
9	Infomedia	"INFOMEDIAR30"	-	Y	-	-	Y	Y	Y	Y	
10	Infosource	"ISSM R02 "	-	Y	-	-	Y	Y	Y	Y	
11	Lead Data	"LEADDATA S04"	-	Y	-	-	Y	Y	Y	Y	
12	MBI	"MBI 01RG40"	-	Y	-	-	Y	Y	Y	Y	
13	MBI	"MBI 01RG50"	-	Y	-	-	Y	Y	Y	Y	
14	MKM	"MCC 03RG20 "	-	Y	-	-	Y	Y	Y	Y	
15	Must	"MUST 007"	-	Y	-	-	Y	Y	Y	Y	
16	MAXELL	"MXL RG04"	-	Y	-	-	Y	Y	Y	Y	
17	OPTODISC	"OPTODISCR016"	-	Y	-	-	Y	Y	Y	Y	
18	PRINCO	"PRINCORGM1"	-	Y	-	-	Y	Y	Y	Y	
19	PRINCO	"PRINCORGM2"	-	Y	-	-	Y	Y	Y	Y	
20	PRODISC	"ProdiscF02"	-	Y	-	-	Y	Y	Y	Y	
21	PRODISC	"ProdiscS05 "	-	Y	-	-	Y	Y	Y	Y	
22	RITEK	"RITEKF1"	-	Y	-	-	Y	Y	Y	Y	
23	RITEK	"RITEKF2"	-	Y	-	-	Y	Y	Y	Y	
24	RITEK	"RITEKM16"	-	Y	-	-	Y	Y	Y	Y	
25	SONY	"SONY16D1"	-	Y	-	-	Y	Y	Y	Y	
26	TMI	"TMI003"	-	Y	-	-	Y	Y	Y	Y	
27	TDK	"TTH02"	-	Y	-	-	Y	Y	Y	Y	
28	TAIYOYUDEN	"TYG03"	-	Y	-	-	Y	Y	Y	Y	
29	Umedisc	"UME02"	-	Y	-	-	Y	Y	Y	Y	

In case of unknown MID, the writing speed is limited to 2x and 4x.



Supported media list of DVD-R on BDR-S11 and BDR-211 series

DVD-R(DL) Ver3.0 (4x Dual Layer format disc)

Writing speed : 2x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	
1	MKM	"MKM 01RD30"	Y	Y	Y	Y	-	-	-	-	
2	PRINCO	"PRINCORDL05"	Y	Y	-	-	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2x.

DVD-R(DL) Ver3.0 (8x Dual Layer format disc)

Writing speed : 2x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	
1	MBI	"MBI 05RD30"	Y	Y	Y	Y	-	-	-	-	
2	MKM	"MKM 03RD30"	Y	Y	Y	Y	-	-	-	-	
3	RITEK	"RITEKP02"	Y	Y	Y	Y	-	-	-	-	
4	TAIYOYUDEN	"TYG11"	Y	Y	Y	Y	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2x.

DVD-R(DL) Ver3.0 (12x Dual Layer format disc)

Writing speed : 2x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Strategy Status								Remarks
			2x	4x	6x	8x	6x	8x	12x	16x	
1	MKM	"MKM 04RD30"	Y	Y	Y	Y	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2x.



Supported media list of DVD-RW on BDR-S11 and BDR-211 series

DVD-RW Ver1.0 (1x format disc)

Writing speed : 1x

No.	Maker	Manufacturer ID	Strategy	Status	1x	2x	4x	6x	Remarks
-----	-------	-----------------	----------	--------	----	----	----	----	---------

In case of unknown MID, the writing speed is limited to 1x.

DVD-RW Ver1.1 (1x format disc)

Writing speed : 1x

No.	Maker	Manufacturer ID	Strategy Status				Remarks
			1x	2x	4x	6x	
1	JVC	"JVC/VictorT7"	Y	-	-	-	
2	RITEK	"RITEK000V11A"	Y	-	-	-	
3	SONY	"SONY000000U9"	Y	-	-	-	

In case of unknown MID, the writing speed is limited to 1x.

DVD-RW Ver1.1 Rev1.0 (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status				Remarks
			1x	2x	4x	6x	
1	SONY	"80SONY-W00-?"	-	Y	-	-	
2	CMC	"CMCW02"	-	Y	-	-	
3	JVC	"JVC_VictorW7"	-	Y	-	-	
4	MBI	"MBI01RWG 10"	-	Y	-	-	
5	MKM	"MCC 01RW11n9"	-	Y	-	-	
6	Panasonic	"MEI 02RW0002"	-	Y	-	-	
7	Panasonic	"MEI 02RW00>R"	-	Y	-	-	
8	MAXELL	"MXLRW001M "	-	Y	-	-	
9	MAXELL	"MXLRW001M X3"	-	Y	-	-	
10	PRODISC	"Prodisc DW04"	-	Y	-	-	
11	RITEK	"RITEKW01"	-	Y	-	-	

In case of unknown MID, the writing speed is limited to 2x.



Supported media list of DVD-RW on BDR-S11 and BDR-211 series

DVD-RW Ver1.1 Rev2.0 (4x format disc)

Writing speed : 2x, 4x

No.	Maker	Manufacturer ID	Strategy Status				Remarks
			1x	2x	4x	6x	
1	CMC	"CMCW03"	-	Y	Y	-	
2	Infomedia	"INFOMEDIAA20"	-	Y	Y	-	
3	JVC	"JVC0VictorD7"	-	Y	Y	-	
4	MBI	"MBI01RWG 20"	-	Y	Y	-	
5	MKM	"MCC 01RW4X "	-	Y	Y	-	
6	OPTODISC	"OPTODISCW004"	-	Y	Y	-	
7	PRINCO	"PRINCORW0004"	-	Y	Y	-	
8	PRODISC	"Prodisc DW06"	-	Y	Y	-	
9	RITEK	"RITEKW04"	-	Y	Y	-	
10	TDK	"TDK60saku"	-	Y	Y	-	

In case of unknown MID, the writing speed is limited to 2x.

DVD-RW Ver1.1 Rev3.0 (6x format disc)

Writing speed : 2x, 4x, 6x

No.	Maker	Manufacturer ID	Strategy Status				Remarks
			1x	2x	4x	6x	
1	JVC	"JVC1Victord7"	-	Y	Y	Y	
2	MKM	"MKM 01RW6X01"	-	Y	Y	Y	
3	RITEK	"RITEKW06"	-	Y	Y	Y	

In case of unknown MID, the writing speed is limited to 2x.



Supported media list of DVD-RAM on BDR-S11 and BDR-211 series

Notice : BDR-211DBK doesn't support DVD-RAM writing function.

DVD-RAM Ver2.1 (2x format disc)

Writing speed : 2x

No.	Maker	Manufacturer ID	Strategy Status			Remarks
			2x	3x	5x	
1	Panasonic	"M01J0005"	Y	-	-	
2	Panasonic	"M01J0008"	Y	-	-	
3	MAXELL	"MXL17"	Y	-	-	

In case of unknown MID, the writing speed is limited to 2x.

DVD-RAM Ver2.x Rev1.0 (3x format disc)

Writing speed : 2x, 3x

No.	Maker	Manufacturer ID	Strategy Status			Remarks
			2x	3x	5x	
1	Panasonic	"M01J3002"	Y	Y	-	
2	Panasonic	"M01J3003"	Y	Y	-	
3	Panasonic	"M01J3004"	Y	Y	-	
4	MAXELL	"MXL8"	Y	Y	-	
5	MAXELL	"MXL9"	Y	Y	-	

In case of unknown MID, the writing speed is limited to 2x.

DVD-RAM Ver2.x Rev2.0 (5x format disc)

Writing speed : 2x, 3x, 5x

No.	Maker	Manufacturer ID	Strategy Status			Remarks
			2x	3x	5x	
1	Panasonic	"M01J5006"	Y	Y	Y	
2	MAXELL	"MXL16"	Y	Y	Y	

In case of unknown MID, the writing speed is limited to 2x.

DVD-RAM Ver2.x Rev5.0 (12x format disc)

Writing speed : Not Supported

No.	Maker	Manufacturer ID	Strategy Status	Remarks
2x	3x	5x		



Supported media list of DVD+R on BDR-S11 and BDR-211 series

DVD+R (2.4x media)

Writing speed : 2.4x

No.	Maker	Manufacturer ID	Media Type /.Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	

In case of unknown MID, the writing speed is limited to 2.4x.

DVD+R (4x media)

Writing speed : 2.4x, 4x

No.	Maker	Manufacturer ID	Media Type /.Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	

In case of unknown MID, the writing speed is limited to 2.4x and 4x.

DVD+R (8x media)

Writing speed : 2.4x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Media Type /.Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	
1	Umedisc	"AML____"	"002"	Y	Y	Y	Y	-	-	-	-	
2	CMC	"CMC MAG_"	"E01"/00	Y	Y	Y	Y	-	-	-	-	other than 00 : 4X
3	Infosource	"ISSM____"	"001"	Y	Y	Y	Y	-	-	-	-	
4	LeadData	"LD____"	"S03"	Y	Y	Y	Y	-	-	-	-	
5	MAXELL	"MAXELL_"	"002"	Y	Y	Y	Y	-	-	-	-	
6	MKM	"MCC_"	"003"	Y	Y	Y	Y	-	-	-	-	
7	Must	"MUST____"	"002"	Y	Y	Y	Y	-	-	-	-	
8	PRODISC	"PRODISC_"	"R03"	Y	Y	Y	Y	-	-	-	-	
9	PHILIPS	"Philips_"	"081"	Y	Y	Y	Y	-	-	-	-	
10	RITEK	"RITEK____"	"R03"/02~	Y	Y	Y	Y	-	-	-	-	00,01 : 4X
11	TAIYOYUDEN	"YUDEN000"	"T02"	Y	Y	Y	Y	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2.4x and 4x.



Supported media list of DVD+R on BDR-S11 and BDR-211 series

DVD+R (16x media)

Writing speed : 2.4x, 4x, 6x, 8x, 12x, 16x

No.	Maker	Manufacturer ID	Media Type / .Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	
1	Umedisc	"AML "	"003"	Y	Y	-	-	Y	Y	Y	Y	
2	CMC	"CMC MAG "	"M01"	Y	Y	-	-	Y	Y	Y	Y	
3	CMC	"CMC MAG "	"M02"	Y	Y	-	-	Y	Y	Y	Y	
4	Daxon	"DAXON "	"AZ3"	Y	Y	-	-	Y	Y	Y	Y	
5	FTI	"FTI "	"016"	Y	Y	-	-	Y	Y	Y	Y	
6	Gigastorage	"GSC503 "	"H02"	Y	Y	-	-	Y	Y	Y	Y	
7	Infomedia	"INFOFME "	"R30"	Y	Y	-	-	Y	Y	Y	Y	
8	Infosource	"ISSM "	"003"	Y	Y	-	-	Y	Y	Y	Y	
9	LeadData	"LD "	"S04"	Y	Y	-	-	Y	Y	Y	Y	
10	MAXELL	"MAXELL "	"003"	Y	Y	-	-	Y	Y	Y	Y	
11	MBI	"MBIPIG101"	"R05"	Y	Y	-	-	Y	Y	Y	Y	
12	MKM	"MCC "	"004"	Y	Y	-	-	Y	Y	Y	Y	
13	Must	"MUST "	"006"	Y	Y	-	-	Y	Y	Y	Y	
14	OPTODISC	"OPTODISC"	"R16"	Y	Y	-	-	Y	Y	Y	Y	
15	PRODISC	"PRODISC "	"R04"	Y	Y	-	-	Y	Y	Y	Y	
16	PRODISC	"PRODISC "	"R05"	Y	Y	-	-	Y	Y	Y	Y	
17	RITEK	"RITEK "	"F16"	Y	Y	-	-	Y	Y	Y	Y	
18	RITEK	"RITEK "	"P16"	Y	Y	-	-	Y	Y	Y	Y	
19	RITEK	"RITEK "	"R05"	Y	Y	-	-	Y	Y	Y	Y	
20	SONY	"SONY "	"D21"	Y	Y	-	-	Y	Y	Y	Y	
21	TDK	"TDK "	"003"	Y	Y	-	-	Y	Y	Y	Y	
22	TAIYOYUDEN	"YUDEN000"	"T03"	Y	Y	-	-	Y	Y	Y	Y	

In case of unknown MID, the writing speed is limited to 2.4x and 4x.



Supported media list of DVD+R on BDR-S11 and BDR-211 series

DVD+R (2.4x media) / Double Layer

Writing speed : 2.4x

No.	Maker	Manufacturer ID	Media Type /.Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	

In case of unknown MID, the writing speed is limited to 2.4x.

DVD+R (8x media) / Double Layer

Writing speed : 2.4x, 4x, 6x, 8x

No.	Maker	Manufacturer ID	Media Type /.Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	
1	CMC	"CMC MAG_"	"D03"/40	Y	Y	Y	Y	-	-	-	-	
2	FTI	"FTI ____"	"R08"/41	Y	Y	Y	Y	-	-	-	-	
3	MBI	"MBIPG101"	"R10"/41	Y	Y	Y	Y	-	-	-	-	
4	MBI	"MBIPG101"	"R12"	Y	Y	Y	Y	-	-	-	-	
5	MKM	"MKM ____"	"003"	Y	Y	Y	Y	-	-	-	-	
6	RITEK	"RITEK ____"	"D03"	Y	Y	Y	Y	-	-	-	-	
7	RITEK	"RITEK ____"	"S04"/42	Y	Y	Y	Y	-	-	-	-	
8	Umedisc	"UMEDISC_"	"DL1"/40	Y	Y	Y	Y	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2.4x.

DVD+R (16x media) / Double Layer

Writing speed : 2.4x

No.	Maker	Manufacturer ID	Media Type /.Rev	Strategy Status								Remarks
				2x	4x	6x	8x	6x	8x	12x	16x	

In case of unknown MID, the writing speed is limited to 2.4x.



Supported media list of DVD+RW on BDR-S11 and BDR-211 series

DVD+RW (2.4x media)

Writing speed : 2.4x

No.	Maker	Manufacturer ID	Media Type / .Rev	Strategy Status					Remarks
				2x	3x	4x	6x	8x	
1	CMC	"CMC MAG_ "	"W01"	Y	-	-	-	-	
2	INFODISC	"INFODISC"	"A01"	Y	-	-	-	-	
3	MBI	"MBIPG101"	"W03"	Y	-	-	-	-	
4	MKM	"MCC_ "	"A01"	Y	-	-	-	-	
5	RITEK	"RITEK_ "	"001"	Y	-	-	-	-	
6	Sentinel	"SENTINEL"	"W01"	Y	-	-	-	-	

In case of unknown MID, the writing speed is limited to 2.4x.

DVD+RW (4x media)

Writing speed : 2.4x, 4x

No.	Maker	Manufacturer ID	Media Type / .Rev	Strategy Status					Remarks
				2x	3x	4x	6x	8x	
1	CMC	"CMC MAG_ "	"W02"	Y	-	Y	-	-	
2	Daxon	"DAXON_ "	"D42"	Y	-	Y	-	-	
3	INFODISC	"INFODISC"	"A10"	Y	-	Y	-	-	
4	MBI	"MBIPG101"	"W04"	Y	-	Y	-	-	
5	MKM	"MKM_ "	"A02"	Y	-	Y	-	-	
6	OPTODISC	"OPTODISC"	"OP4"	Y	-	Y	-	-	
7	RICOH	"RICOHJPN"	"W11"	Y	-	Y	-	-	
8	RITEK	"RITEK_ "	"004"	Y	-	Y	-	-	
9	SONY	"SONY_ "	"S11"	Y	-	Y	-	-	

In case of unknown MID, the writing speed is limited to 2.4x.

DVD+RW (3.3x-8x media)

Writing speed : 3.3x, 6x, 8x

No.	Maker	Manufacturer ID	Media Type / .Rev	Strategy Status					Remarks
				2x	3x	4x	6x	8x	
1	CMC	"CMC MAG_ "	"W03"	-	Y	-	Y	Y	
2	MKM	"MKM_ "	"A03"	-	Y	-	Y	Y	
3	RICOH	"RICOHJPN"	"W21"	-	Y	-	Y	Y	
4	RITEK	"RITEK_ "	"008"	-	Y	-	Y	-	

In case of unknown MID, the writing speed is limited to 3.3x.



Supported media list of CD-R on BDR-S11 and BDR-211 series

CD-R Media:

Writing speed : 4x, 10x, 16x, 24x, 32x, 40x

No.	Manufacturer	Name	Lead In Start Time	Lead Out Start Time	Strategy Status								Remarks	
					CAV		CAV		CAV		CAV			
					4x	10x	16x	24x	32x	16x	24x	32x	40x	
1	4M	x52 Phthalocyanine 80	97:28:26	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
2	CMC	x52 80	97:26:66	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
3	CMC	x52 80	97:26:66	79:59:71	Y	Y	-	-	-	Y	Y	Y	Y	
4	CMC	x48 Phthalocyanine 80	97:26:66	79:59:71	Y	Y	-	-	-	Y	Y	Y	Y	
5	CMC	x48 Phthalocyanine 80	97:26:66	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
6	CMC	x24 Phthalocyanine 80	97:26:66	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
7	CMC	x16 Phthalocyanine 80	97:26:66	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
8	Daxon (ACER)	X48/52 Phthalocyanine 80	97:22:67	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
9	Daxon (ACER)	X40 Phthalocyanine 80	97:22:67	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
10	Daxon (ACER)	X32 Phthalocyanine 80	97:22:67	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
11	EMTEC (Plasmon)	52x 80	97:27:18	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
12	E-Top	52x Cyanine	97:21:22	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
13	E-Top	52x Phthalocyanine 80	97:21:28	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
14	Gigastorage	Cyanine 80	97:28:12	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
15	Gigastorage	Phthalocyanine 80	97:28:15	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
16	Lead Dada	x32 Phthalocyanine 80	97:26:56	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
17	Lead Dada	x48 Phthalocyanine 80	97:24:16	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
18	MAXELL	CD-R74 (=23)	97:25:22	74:30:00	Y	Y	-	-	-	Y	Y	Y	Y	
19	MAXELL	74 Data	97:25:23	74:30:00	Y	Y	-	-	-	Y	Y	Y	Y	
20	MAXELL	80 Data	97:25:23	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
21	MAXELL	Cyanine 74	97:25:24	74:30:00	Y	Y	-	-	-	Y	Y	Y	Y	
22	MAXELL	Cyanine 80	97:25:24	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
23	MBI	x52 80	97:17:06	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
24	MBI	x48 Phthalocyanine 80	97:17:06	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
25	MCC(MITSUBISHI)	Supper-Azo 80	97:15:21	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
26	MCC(MITSUBISHI)	Supper-Azo 74	97:34:21	74:43:00	Y	Y	-	-	-	Y	Y	Y	Y	
27	MCC(MITSUBISHI)	Super-Azo HG80	97:34:22	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
28	MCC(MITSUBISHI)	48x SONIC-Azo 80	97:34:23	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
29	MCC(MITSUBISHI)	Supper-Azo HGX80	97:34:23	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
30	NAN-YA Plastics	Ever Media	97:15:37	79:59:74	Y	Y	-	-	-	Y	Y	Y	-	
31	PRINCO	CDR-74	97:27:28	74:50:01	Y	Y	-	-	-	Y	Y	Y	Y	
32	PRINCO	CDR-80	97:27:28	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
33	PRODISC	74	97:32:19	74:30:00	Y	Y	-	-	-	Y	Y	Y	Y	
34	PRODISC	74Audio	97:32:19	74:30:00	Y	Y	-	-	-	Y	Y	Y	Y	
35	PRODISC	x52 Phthalocyanine 80	97:32:19	79:59:71	Y	Y	-	-	-	Y	Y	Y	Y	
36	PRODISC	x48 Phthalocyanine 80	97:32:19	79:59:72	Y	Y	-	-	-	Y	Y	Y	Y	
37	PRODISC	x40 Phthalocyanine 80	97:32:19	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
38	PRODISC	x24 Phthalocyanine 80	97:32:19	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
39	PRODISC	80	97:32:19	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	

In case of unknown media, the writing speed is limited to 32x.



Supported media list of CD-R on BDR-S11 and BDR-211 series

CD-R Media:

Writing speed : 4x, 10x, 16x, 24x, 32x, 40x

No.	Manufacturer	Name	Lead In Start Time	Lead Out Start Time	Strategy Status								Remarks	
					4x	10x	16x	24x	32x	16x	24x	32x	40x	
40	RITEK	G Type80	97:15:17	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
41	RITEK	H Type74	97:31:01	74:45:00	Y	Y	-	-	-	Y	Y	Y	Y	
42	RITEK	G Type74	97:31:07	74:45:00	Y	Y	-	-	-	Y	Y	Y	Y	
43	RITEK	H Type80	97:15:11	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
44	RITEK	S Type80	97:15:12	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
45	RITEK	K Type80	97:15:12	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
46	RITEK	48x JS Type80	97:15:17	79:59:70	Y	Y	-	-	-	Y	Y	Y	Y	
47	RITEK	JS Type80	97:15:17	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
48	RITEK	S Type74	97:31:01	74:45:01	Y	Y	-	-	-	Y	Y	Y	Y	
49	RITEK	K Type74	97:31:02	74:45:00	Y	Y	-	-	-	Y	Y	Y	Y	
50	RITEK	JS Type74	97:31:07	74:45:01	Y	Y	-	-	-	Y	Y	Y	Y	
51	RITEK	JS Type74	97:31:07	74:45:02	Y	Y	-	-	-	Y	Y	Y	Y	
52	SKC	x52 Phthalocyanine	97:26:26	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
53	SKC	x32 Phthalocyanine	97:26:26	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
54	SKC	Phthalocyanine	97:26:26	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
55	SONY	X32 Cyanine	97:24:12	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
56	SONY	x48/52 Phthalocyanine	97:24:16	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
57	SONY	74	97:24:11	74:43:00	Y	Y	-	-	-	Y	Y	Y	Y	
58	SONY	74Audio	97:24:11	74:43:00	Y	Y	-	-	-	Y	Y	Y	Y	
59	SONY	80	97:24:11	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
60	TaiyoYuden	74P	97:24:01	74:43:00	Y	Y	-	-	-	Y	Y	Y	Y	
61	TaiyoYuden	X40NEW	97:24:01	74:43:02	Y	Y	-	-	-	Y	Y	Y	Y	
62	TaiyoYuden	74X	97:24:01	74:43:01	Y	Y	-	-	-	Y	Y	Y	Y	
63	TaiyoYuden	X40NEW	97:24:01	79:59:72	Y	Y	-	-	-	Y	Y	Y	Y	
64	TaiyoYuden	32x 80X	97:24:01	79:59:73	Y	Y	-	-	-	Y	Y	Y	Y	
65	TaiyoYuden	80P	97:24:01	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
66	TDK	CD-R80(15)	97:15:00	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
67	TDK	X40 Phthalocyanine	97:15:05	91:01:48	Y	Y	-	-	-	Y	Y	Y	Y	
68	TDK	X48/52 Phthalocyanine	97:15:05	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
69	TDK	CD-R80(25)	97:25:00	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
70	TDK	CD-R74	97:32:00	74:59:00	Y	Y	-	-	-	Y	Y	Y	Y	
71	TDK	X48 Phthalocyanine	97:32:05	74:59:00	Y	Y	-	-	-	Y	Y	Y	Y	
72	TDK	CD-R63S	97:49:00	63:52:00	Y	Y	-	-	-	Y	Y	Y	-	
73	TDK	Cyanine 80	97:15:01	79:59:74	Y	Y	-	-	-	Y	Y	Y	Y	
74	TDK	Cyanine 74	97:32:01	74:59:00	Y	Y	-	-	-	Y	Y	Y	Y	

In case of unknown media, the writing speed is limited to 32x.



Supported media list of CD-RW on BDR-S11 and BDR-211 series

CD-RW : Normal Speed (4x)

Writing speed : 4x

No.	Manufacturer	Capacity (min) / (MB)	Lead In	Lead Out	Strategy Status				Remarks
			Start Time	Start Time	4x	10x	16x	24x	
1	RICOH		97:27:00	74:12:00	Y	-	-	-	
2	MCC	74/650	97:34:22	74:43:00	Y	-	-	-	
3	MCC	80/700	97:34:22	79:59:74	Y	-	-	-	
4	SONY		97:26:51	79:59:74	Y	-	-	-	
5	RITEK	80/700	97:10:00	79:59:74	Y	-	-	-	
6	RITEK		97:27:10	74:41:00	Y	-	-	-	
7	CMC	80/700	97:26:65	79:59:74	Y	-	-	-	
8	CMC	74/650	97:26:65	75:00:00	Y	-	-	-	
9	DAXON (ACER)		97:22:60	74:41:50	Y	-	-	-	
10	Prodisc	80/700	97:32:11	79:59:74	Y	-	-	-	
11	Gigastorage		97:28:15	79:59:74	Y	-	-	-	
12	SKC		97:26:20	74:59:73	Y	-	-	-	
13	LEAD DATA		97:26:50	79:59:74	Y	-	-	-	
14	PRINCO		97:27:21	79:59:74	Y	-	-	-	
15	Moser Baer		97:17:00	79:59:74	Y	-	-	-	
16	Infodisc (Memolex)	80/700	97:25:30	79:59:74	Y	-	-	-	
17	Infodisc (Memolex)	74/650	97:25:30	74:41:47	Y	-	-	-	

In case of unknown MID, the writing speed is limited to 4x.



Supported media list of CD-RW on BDR-S11 and BDR-211 series

CD-RW : High Speed (4X--10X)

Writing speed : 4x, 10x

No.	Manufacturer	Capacity (min) / (MB)	Lead In Start Time	Lead Out Start Time	Strategy Status				Remarks
					4x	10x	16x	24x	
1	RICOH	74/650	97:27:00	74:12:00	Y	Y	-	-	
2	MCC	74/650	97:34:23	74:43:00	Y	Y	-	-	
3	MCC	80/700	97:34:23	79:59:74	Y	Y	-	-	
4	SONY		97:27:00	74:12:00	Y	Y	-	-	
5	SONY		97:34:23	74:43:00	Y	Y	-	-	
6	RITEK / (TDK)	80/700	97:10:00	79:59:74	Y	Y	-	-	
7	RITEK		97:27:10	74:41:00	Y	Y	-	-	
8	CMC	80/700	97:26:65	79:59:74	Y	Y	-	-	
9	CMC		97:26:65	75:00:00	Y	Y	-	-	
10	DAXON (ACER)		97:22:60	74:41:50	Y	Y	-	-	
11	DAXON (ACER)		97:22:62		Y	Y	-	-	
12	Imation		97:24:15	74:30:00	Y	Y	-	-	
13	Prodisc	80/700	97:32:12	79:59:74	Y	Y	-	-	
14	Gigastorage		97:28:15	74:12:00	Y	Y	-	-	
15	SKC		97:26:21	74:59:73	Y	Y	-	-	
16	LEAD DATA	80/700	97:26:51	79:59:74	Y	Y	-	-	
17	Moser Baer	80/700	97:17:01	79:59:74	Y	Y	-	-	
18	Infodisc(memolex)	80/700	97:25:30	79:59:73	Y	Y	-	-	

In case of unknown MID, the writing speed is limited to 4x, 10x.



Supported media list of CD-RW on BDR-S11 and BDR-211 series

CD-RW : Ultra Speed (24X media)

Writing speed : 10x, 16x, 24x

No.	Manufacturer	Capacity (min) / (MB)	Lead In Start Time	Lead Out Start Time	Strategy Status				Remarks
					4x	10x	16x	24x	
1	MCC	80/700	97:34:24	79:59:74	-	Y	Y	Y	
2	MCC	74/650	97:34:24	74:43:00	-	Y	Y	Y	
3	RITEK		97:10:02	79:59:74	-	Y	Y	Y	
4	RITEK	74/650	97:27:12	74:41:00	-	Y	Y	Y	
5	CMC	74/650	97:26:67	75:00:00	-	Y	Y	Y	
6	CMC	80/700	97:26:67		-	Y	Y	Y	
7	Prodisc		97:32:12	79:59:73	-	Y	Y	Y	
8	SKC		97:26:23	74:59:73	-	Y	Y	Y	
9	NANYA		97:15:36	74:41:00	-	Y	Y	Y	

In case of unknown MID, the writing speed is limited to 10x, 16x, 24x.

CD-RW : Ultra Speed+ (32X media)

Writing speed : 16x, 24x

No.	Manufacturer	Capacity (min) / (MB)	Lead In Start Time	Lead Out Start Time	Strategy Status				Remarks
					4x	10x	16x	24x	
1	MCC	74/650	97:34:25	74:43:00	-	-	Y	Y	
2	MCC	80/700	97:34:25	79:59:74	-	-	Y	Y	
3	CMC	80/700	97:26:67	79:59:64	-	-	Y	Y	
4	Daxon	74/650	97:22:60	74:41:50	-	-	Y	Y	

In case of unknown MID, the writing speed is limited to 16x, 24x.